



# **SNS COLLEGE OF TECHNOLOGY**

**Coimbatore-35**  
**An Autonomous Institution**

Accredited by NBA – AICTE and Accredited by NAAC – UGC with 'A+' Grade  
Approved by AICTE, New Delhi & Affiliated to Anna University, Chennai



## **DEPARTMENT OF BIOMEDICAL ENGINEERING**

### **19BMB302 - BIOMEDICAL SIGNAL PROCESSING**

**III YEAR/ V SEMESTER**

## **Unit V : DATA REDUCTION TECHNIQUES**



- Turning point algorithm
- AZTEC algorithm
- CORTES algorithm
- Fan algorithm
- Huffman algorithm



# Turning point algorithm



- The original motivation for the turning point (TP) algorithm was to reduce the sampling frequency of an ECG signal from 200 to 100 samples/s.
- The algorithm developed from the observation that, except for QRS complexes with large amplitudes and slopes, a sampling rate of 100 samples/s is adequate.
- TP is based on the concept that ECG signals are normally oversampled at four or five times faster than the highest frequency present.
- For example, an ECG used in monitoring may have a bandwidth of 50 Hz and be sampled at 200 sps in order to easily visualize the higher-frequency attributes of the QRS complex.
- Sampling theory tells us that we can sample such a signal at 100 sps.
- TP provides a way to reduce the effective sampling rate by half to 100 sps by selectively saving important signal points



# Turning point algorithm

- The algorithm processes three data points at a time. It stores the first sample point and assigns it as the reference point  $X_0$ . The next two consecutive points become  $X_1$  and  $X_2$ .
- The algorithm retains either  $X_1$  or  $X_2$ , depending on which point preserves the turning point (i.e., slope change) of the original signal.
- Figure 1 shows all the possible configurations of three consecutive sample points.

1		4		7	
2		5		8	
3		6		9	

- In each frame, the solid point preserves the slope of the original three points.



- The algorithm saves this point and makes it the reference point  $X_0$  for the next iteration.
- It then samples the next two points, assigns them to  $X_1$  and  $X_2$ , and repeats the process.
- We use a simple mathematical criterion to determine the saved point.
- First consider a  $sign(x)$  operation

$$sign(x) = \begin{cases} 0 & x = 0 \\ +1 & x > 0 \\ -1 & x < 0 \end{cases}$$



1		4		7	
2		5		8	
3		6		9	

Pattern	$s_1 = \text{sign}(X_1 - X_0)$	$s_2 = \text{sign}(X_2 - X_1)$	NOT( $s_1$ ) OR ( $s_1 + s_2$ )	Saved sample
1	+1	+1	1	$X_2$
2	+1	-1	0	$X_1$
3	+1	0	1	$X_2$
4	-1	+1	0	$X_1$
5	-1	-1	1	$X_2$
6	-1	0	1	$X_2$
7	0	+1	1	$X_2$
8	0	-1	1	$X_2$
9	0	0	1	$X_2$



- We then obtain  $s1 = \text{sign}(X1 - X0)$  and  $s2 = \text{sign}(X2 - X1)$ , where  $(X1 - X0)$  and  $(X2 - X1)$  are the slopes of the two pairs of consecutive points.
- If a slope is zero, this operator produces a zero result. For positive or negative slopes, it yields +1 or -1 respectively.
- A turning point occurs only when a slope changes from positive to negative or vice versa.
- We use the logical Boolean operators, NOT and OR, as implemented in the C language to make the final judgment of when a turning point occurs.



- In the C language,  $\text{NOT}(c) = 1$  if  $c = 0$ ; otherwise  $\text{NOT}(c) = 0$ .
- Also logical OR means that  $(a \text{ OR } b) = 0$  only if  $a$  and  $b$  are both 0.
- Thus, we retain  $X1$  only if  $\{\text{NOT}(s1) \text{ OR } (s1 + s2)\}$  is zero, and save  $X2$  otherwise.
- In this expression,  $(s1 + s2)$  is the arithmetic sum of the signs produced by the *sign* function.
- The final effect of this processing is a Boolean decision whether to save  $X1$  or  $X2$ .
- Point  $X1$  is saved only when the slope changes from positive to negative or vice versa.
- This computation could be easily done arithmetically, but the Boolean operation is computationally much faster.





## Advantages

- The TP algorithm is simple and fast, producing a fixed reduction ratio of 2:1.
- After selectively discarding exactly half the sampled data, we can restore the original resolution by interpolating between pairs of saved data points.

## Disadvantages

- The resulting reconstructed signal typically has a widened QRS complex and sharp edges that reduce its clinical acceptability.
- Another disadvantage of this algorithm is that the saved points do not represent equally spaced time intervals. This introduces short term time distortion.



# Thank You!