



SNS COLLEGE OF ENGINEERING
(Autonomous)
DEPARTMENT OF CSE - IoT

COURSE NAME:19EC306 / DIGITAL CIRCUITS
II YEAR/III SEMESTER

UNIT:1- MINIMIZATION TECHNIQUES AND LOGIC GATES

TOPIC:BOOLEAN POSTULATES AND LAWS



Outline

- 1854: Logical algebra was published by **George Boole** → known today as “Boolean Algebra”
 - It’s a convenient way and systematic way of expressing and analyzing the operation of logic circuits.
- 1938: **Claude Shannon** was the first to apply Boole’s work to the analysis and design of logic circuits.

Boolean operations and expressions



- *Variable* – a symbol used to represent a logical quantity.
- *Complement* – the inverse of a variable and is indicated by a bar over the variable.
- *Literal* – a variable or the complement of a variable.

Basic Identities of Boolean Algebra



$$1. X + 0 = X$$

$$2. X + 1 = 1$$

$$3. X \cdot 0 = 0$$

$$4. X \cdot 1 = X$$

$$5. X + X = X$$

$$6. X \cdot X = X$$

$$7. X + X' = 1$$

$$8. X \cdot X' = 0$$

Basic Identities of Boolean Algebra



Laws of Commutativity

$$1. X + Y = Y + X$$

$$2. XY = YX$$

Laws of Associativity

$$1. X + (Y + Z) = (X + Y) + Z$$

$$2. X(YZ) = (XY)Z$$

Boolean function and truth table



Laws of Distributivity



1. $X (Y + Z) = XY + XZ$
2. $X + YZ = (X + Y) (X + Z)$

De Morgan's Theorem

1. $(X + Y)' = X'Y'$
2. $(XY)' = X' + Y'$

Law of Involution

1. $(X')' = X$



DeMorgan's Theorems

- The complement of two or more ANDed variables is equivalent to the OR of the complements of the individual variables.

$$\overline{X \bullet Y} = \bar{X} + \bar{Y}$$

The left side of the equation is enclosed in a red dashed circle and labeled "NAND". The right side is enclosed in a green dashed circle and labeled "Negative-OR".

- The complement of two or more ORed variables is equivalent to the AND of the complements of the individual variables.

$$\overline{X + Y} = \bar{X} \bullet \bar{Y}$$

The left side of the equation is enclosed in an orange dashed circle and labeled "NOR". The right side is enclosed in a blue dashed circle and labeled "Negative-AND".

Boolean function minimization using Boolean algebra



- Apply DeMorgan's theorems to the expressions:

$$\overline{X \cdot Y \cdot Z}$$

$$\overline{X + Y + Z}$$

$$\overline{\bar{X} + \bar{Y} + \bar{Z}}$$

$$\overline{\bar{W} \cdot \bar{X} \cdot \bar{Y} \cdot \bar{Z}}$$



Thank
you

14/09/23

Minimization techniques and logic gates/19EC306 –Digital
Circuits/Dr. J. Grace Jency/CSE - IoT/SNSCE
Minimization techniques and logic
gates/19EC306 –Digital
Circuits/S.Jayashree/CSD/SNSCE